

Model	MAX Watts (W)	Voltage Range(V)	Max Current(A)	Rotor Poles	No load Current(A)	Resistance ( $\Omega$ )	Kv (RPM/Volt)	Motor Size (mm)	Stator Size(mm)	Weight (g)	Propeller (Inch)
C2830-06	340	7~12	28	14	1.4	0.035	2200	$\varnothing$ 28x30	$\varnothing$ 22 x 12	57	9x 6/10x 5/10x 6
C2830-09	300	7~12	25	14	1.2	0.085	1300	$\varnothing$ 28x30	$\varnothing$ 22 x 12	57	9x 6/10x 5/10x 6
C2830-12	260	7~15	21	14	0.9	0.152	1000	$\varnothing$ 28x30	$\varnothing$ 22 x 12	57	9x 4.5/10x 6/10x 5
C2830-14	240	7~15	19	14	0.6	0.189	850	$\varnothing$ 28x30	$\varnothing$ 22 x 12	57	11x 5.5/9x 6/10x 4
C2830-15	230	7~15	18	14	0.6	0.221	750	$\varnothing$ 28x30	$\varnothing$ 22 x 12	57	11x 5.5/10x 7
C2834-08	380	7~15	26	14	1.2	0.068	1120	$\varnothing$ 28x34	$\varnothing$ 22 x 16	67	9x 6/10x 4/11x 5.5
C2834-10	340	7~18	22	14	0.8	0.108	880	$\varnothing$ 28x34	$\varnothing$ 22 x 16	67	11x 8.5/10x 7/12x 6
C2834-12	300	7~18	19	14	0.6	0.152	750	$\varnothing$ 28x34	$\varnothing$ 22 x 16	67	11x 8.5/11x 10/12x 6

